


4005 FIRE ALARM SYSTEM OPERATING INSTRUCTIONS FOLLOWING AN ALARM/TROUBLE/SUPERVISORY CONDITION



YOUR SAFETY, AS WELL AS THE SAFETY OF THOSE AROUND YOU, ALWAYS COMES FIRST.
Actions taken during a fire depend upon local practices. Be sure you know what to do.

ALARM	TROUBLE/SUPERVISORY
<p style="text-align: center;">RED LED FLASHES AND TONE-ALERT PULSES</p> <div style="border: 1px solid black; padding: 5px; margin-bottom: 10px;"> <p style="text-align: center;">FIRE = 3 SUPERVISORY = 0 TROUBLE = 0 FIRE ZONES: 02 07 06</p> </div> <p>1. Unlock and open the panel door. <i>Read</i> and follow the instructions on the display. It will toggle between Screens 1 and 2.</p> <p>SCREEN 1</p> <div style="border: 1px solid black; padding: 5px; margin-bottom: 10px;"> <p style="text-align: center;">FIRE = 3 SUPERVISORY = 0 TROUBLE = 0 FIRE ZONES 02 07 06</p> </div> <p>SCREEN 2</p> <div style="border: 1px solid black; padding: 5px; margin-bottom: 10px;"> <p style="text-align: center;">FIRE = 3 SUPERVISORY = 0 TROUBLE = 0 **FIRE** Press ACK to review</p> </div> <p>2. Press the (ALARM ACK) key under the flashing red LED. <i>Read</i> the alphanumeric display.</p> <ul style="list-style-type: none"> - The tone-alert is silenced and the display shows pertinent report information, such as shown in Screen 3. <p>SCREEN 3</p> <div style="border: 1px solid black; padding: 5px; margin-bottom: 10px;"> <p style="text-align: center;">First Floor East Wing Room 12 Smoke Detector Alarm 1/3</p> </div> <p>3. <i>Read</i> the Alarm Information on the display. Summon appropriate personnel to respond.</p> <p>HOW TO SILENCE THE SIGNALS</p> <p>4. Press the (ALARM SILENCE) key and read the display. The alphanumeric display shows signal status.</p> <ul style="list-style-type: none"> - ALARM SILENCED LED turns ON. <p>HOW TO RESET THE SYSTEM</p> <p>5. When the alarm condition has been cleared, restore or replace all affected devices (smoke detectors, pull stations, etc.) in accordance with the instructions provided with each device.</p> <p>6. Reset the system.</p> <ul style="list-style-type: none"> - Press the (SYSTEM RESET) key. <p>The system displays Screen 4 after a completed System Reset with no alarms present.</p> <p>SCREEN 4</p> <div style="border: 1px solid black; padding: 5px; margin-bottom: 10px;"> <p style="text-align: center;">No Alarms Present, System Reset Complete Restore previous screen, press any key</p> </div> <p>7. Press any key to return to the SYSTEM NORMAL screen.</p>	<p style="text-align: center;">YELLOW LED FLASHES AND TONE-ALERT SOUNDS</p> <div style="border: 1px solid black; padding: 5px; margin-bottom: 10px;"> <p style="text-align: center;">FIRE = 0 SUPERVISORY = 0 TROUBLE = 3 ** TROUBLE ** Press ACK to review</p> </div> <p>Note: A Trouble Condition is described in this example. A Supervisory Condition is handled in a similar manner.</p> <p>1. Unlock and open panel door. <i>Read</i> and follow the instructions on the display (see Screen 1 for an example).</p> <p>SCREEN 1</p> <div style="border: 1px solid black; padding: 5px; margin-bottom: 10px;"> <p style="text-align: center;">FIRE = 0 SUPERVISORY = 0 TROUBLE = 3 ** TROUBLE ** Press ACK to review</p> </div> <p>2. Press the (TROUBLE ACK) key under the flashing yellow LED. <i>Read</i> the Trouble information on the display (see Screen 2 for an example).</p> <p>SCREEN 2</p> <div style="border: 1px solid black; padding: 5px; margin-bottom: 10px;"> <p style="text-align: center;">First Floor East Wing Room 12 Smoke Detector Trouble 1/3</p> </div> <p>3. Summon appropriate personnel to respond.</p> <p>4. Ensure that response personnel restores or replaces the defective device (switch, wire, notification appliance, etc.) in accordance with device instructions.</p> <ul style="list-style-type: none"> - If necessary, press (SYSTEM RESET) when the abnormal condition has been corrected. - After a short delay, the system returns to normal and displays a screen similar to Screen 3. <p>SCREEN 3</p> <div style="border: 1px solid black; padding: 5px; margin-bottom: 10px;"> <p style="text-align: center;">** SYSTEM IS NORMAL ** 12:30:02pm Thu 20-July-95</p> </div> <p>Note: If your system configuration does not match this sheet, consult Simplex for specific operations. Simplex is listed in the Yellow Pages.</p> <p>In case of trouble, notify:</p> <p>Name _____</p> <p>Address _____</p> <p>Phone # _____</p>
<p>THESE INSTRUCTIONS ARE INTENDED TO BE FRAMED AND MOUNTED ADJACENT TO THE CONTROL PANEL FOR READY REFERENCE.</p> <p>See Operator's Instruction Manual for detailed operation.</p>	

