

VISTA-50P CONTROL PANEL



Honeywell's VISTA-50P Control Panel provides the flexibility of up to eight independent partitions with the economy of a single control.

FEATURES

Dependable features to meet your most demanding installations:

- Nine hardwired zones standard
- Expandable to 87 total zones
- Eight partitions standard
- 75 user codes work in all partitions
- Seven authority levels
- 224 event memory log/printer option
- Four trigger outputs
- 5800 Series wireless compatibility
- Supports two-wire multiplex
- Scheduling of events (real time clock)
- Keypad macro features
- Master console option for viewing all partitions at a glance
- Common lobby logic
- Fast downloading
- Supports up to 16 relays and/or X-10
- Quick start programming
- False alarm features
- UL Commercial Burglary listed (VISTA-50PUL)

End users will appreciate the easy-to-use convenience and control features of the VISTA-50P:

- Wireless remote controls (featuring single button system operation):
 - 5804 - Four-Button Wireless Key
 - 5804BD - Bidirectional Four-Button Wireless Key with system status feedback
- Single or dual-button wireless personal panic:
 - 5802MN
 - 5802MN2
- Home control features activate lights, appliances, garage doors and numerous other devices
- The VISTA Interactive Phone Module (VIP) gives the end-user control of their system from any touchtone phone. The 4286 VIP responds in English, with a vocabulary of over 100 words
- Full English display keypads for clear understanding of system status and zone locations
- Timed event applications:
 - Opens garage doors and turns on lights
 - Provides "lived-in look" while away from home
 - Ability to limit access to parts of the home at certain times

VISTA-50P

CONTROL PANEL

SPECIFICATIONS

Electrical

- Aux power 12VDC, 750mA max
- 16.5 VAC/40 VA transformer
- Alarm output 12VDC, 1.7 Amps max
- For UL installations, combined Aux and alarm output cannot exceed 750mA

Output Control

- Supports up to four relay boards (Part No. 4204)
- Each board supports four relays for a total of 16
- Optional X-10 interface (Part No. 4300) may be used to control X-10 receiving devices
- Each X-10 receiver address counts as one relay when computing total relays
- Real time clock can be used for relay/X-10 control

Zones

- Nine hardwired zones
- Selectable response on zone 9: 10MSec or 500MSec
- Assignable to any partition
- 14 zone types to choose from

- Programmable swinger suppression

Communications

- Touchtone or pulse
- Formats supported: ADEMCO Contact ID, ADEMCO 4 + 2 Express, ADEMCO low speed
- 3+1, 4+1 and 4+2 reporting
- Reporting capabilities: Split, Dual, Split/Dual
- Low battery reports 11.2-11.6VDC
- Expanded reporting
- Up to four digit PABX codes supported
- True dial tone detection
- Double pole line seizure
- AC loss and restoral reporting supported

Supported Devices

Hardwired Expansion Devices

- 4208U Eight-Zone Expansion Module
- Keypads
 - 6139 Custom English (required for programming) -100mA
 - 6128 Fixed English LCD - 30mA
- Voice Module 4286 VIP-160mA
- Two-Wire Smoke Detectors

- Duct Detectors

- Serial Printer

- Polling Loop Devices

- Key Switch Devices

Wireless Receiver Systems

- 5800 Series
 - 5881ENL up to 8 zones-50mA
 - 5881ENM up to 16 zones-50mA
 - 5881ENH up to 26 zones-50mA
- All Receivers Support:
 - Diversity reception with two antennae
 - Remote mounting for best location
 - Use of second receiver for maximum coverage or tough installations
 - Unique supervision and low battery indications by point

Transmitters

- 5800 Series
 - Three volt Duracell lithium batteries
 - One mile range
 - Tamper standard

Agency Listings

- UL Residential Fire and Burglary and CSFM
- UL Commercial Burglary (VISTA-50PUL)

ORDERING

VISTA-50P

Control Panel

Automation and Control Solutions

Honeywell Security & Communications
2 Corporate Center Dr. Suite 100
P.O. Box 9040
Melville, NY 11747
www.honeywell.com

L/VIS50P/D
September 2008
© 2008 Honeywell International Inc.

Honeywell

www.BevanSecurity.Com