

VISTA-15P

CONTROL PANEL



Honeywell's versatile VISTA-15P is the ideal choice for any residential installation. VISTA-15P gives you the ability to send alarm signals and upload/download via an Internet Protocol (IP), improving the speed at which information can be delivered to and from the control panel. In addition, when used with an AlarmNet Internet or digital communicator, the VISTA-15P can be installed in premises without TELCO lines – guaranteeing communication independent of any home infrastructure. Hardwired expansion, graphic keypad support, two-wire smoke detectors, scheduling options and a host of end-user and installer features separate the VISTA-15P from all other six-zone panels – offering you and your customers the most panel for the dollar.

FEATURES

- IP alarm reporting and uploading/downloading capability for Internet and Intranet use via 7845i, 7845i-ENT, 7845GSMR or 7845i-GSM
 - Six on-board hardwired zones
 - 16 hardwired expansion zones totalling 22
 - 26 wireless expansion zones
 - Supports two graphic touchscreen keypads
 - Eight independent keyfob zones allow wireless keys to be programmed without using any of the 26 zones
 - Eight output devices
 - Relays (Model 4204 Relay Modules, or 4229 Expansion Module), and/or
 - X-10® devices (when used with a 1361X10 Transformer)
 - Two low current on-board trigger outputs
 - 50 Event Log viewable at system keypads with time/date stamp
 - 32 system user codes
 - Two installer configurable zone types allows the installer to "create custom zone types" by assigning all zone attributes
 - Multiple actions on output devices depending on system "state"
 - Turns light off when system arms
 - Turns same lights on when system disarms
 - Flashes same lights when system is in alarm
 - Built-in phone line cut monitor with programmable delay and annunciation options
 - Display on system keypads
 - Trigger local sounders
 - Trigger system bell
 - Supports four-wire and up to 16 two-wire smokes
 - Works with Sentrol CleanMe™ maintenance signal
 - User Scheduling
 - Automatically activates X-10 and relays at programmed times
 - Latchkey reports to pagers
 - Auto arm/disarm
 - "User access" time windows
 - Supports up to two numeric pagers
 - VIP Module allows system control from any touchtone phone
 - Chime by zone
- Security Dealer Features**
- Automatic System Load Shed
 - During extended AC power fail, the system battery will be disconnected to prevent irreversible battery failure. Reduces service calls to replace batteries.
 - Dynamic Signaling
 - Reduces redundant reporting to the central station when multiple reporting methods are used; i.e. digital dialer and AlarmNet Radio
- *requires custom alpha keypad
- Valuable End-User Features**
- Now viewable on system keypads:
 - Exit countdown
 - Time and date display*
 - Event log*
 - Auto keypad backlighting on entry
 - Keyswitch arming
 - Programmable macro buttons and single-button arming
 - A variety of wireless remote controls for single-button operation

VISTA-15P

CONTROL PANEL

SPECIFICATIONS

Electrical

- Aux. power 12VDC, 600mA maximum
- Seven hour standby at 400mA aux. load with four amp hour battery
- 16.5VAC/25VA transformer
- Alarm output 12VDC, 2.0A maximum
- For UL installations, combined aux. and alarm output cannot exceed 700mA

Output Control

- Supports a maximum of eight output devices (combination of relays and/or X-10) plus two onboard triggers

Zones

- Six hardwired zones
- Selectable response: 10msec, 350msec, 750msec
- 16 selectable zone types plus two configurable zone types
- Programmable swinger suppression

Expansion Devices

- 4219 – Eight hardwired zones – 16mA
- 4204 – Up to four relays – 15mA standby (each active relay draws an additional 40mA)
- 4229 – Eight hardwired zones and two relays – 36mA (each active relay draws an additional 40mA)

Accessories

- 7845i Internet Communicator
- 7845i-ENT Enterprise Internet Communicator
- 7845GSMR Dual-Path Digital Wireless Communicator
- 7845i-GSM Triple-Path Digital Communicator
- 4286 VIP Voice Module – 220mA
- 5881ENL supports up to eight zones – 5881ENM Supports up to 16 zones – 60mA
- 5881ENH Supports up to 32 zones – 50mA
- 5883 Transceiver supports up to 26 zones – 80mA
- Supports Eagle 1225 and 1221 boards

Keypads

- 6160 Custom Alpha (required for programming) – 100mA
- 6160V Custom Alpha Voice – 100mA
- 6150 Fixed English LCD – 85mA/40mA
- 6150V Fixed English Voice LCD – 85mA/40mA
- 6150RF Fixed English RF LCD – 85mA/40mA
- 6148 Fixed English LCD – 70mA/30mA
- 6270 Graphic Touchscreen
- 6271V Graphic Touchscreen with Voice
- 6271C Color Graphic Touchscreen
- 6271CV Color Graphic Touchscreen with Voice
- 8132 Advanced User Interface

Agency Listings

- UL Residential Fire, Burglary and CSFM
- ETL Residential Fire, Burglary

Smoke Detectors

- Supports up to 16 two-wire smoke detectors
- Supports four-wire smoke detectors

Communications

- 7845i Internet Communicator
- 7845i-ENT Enterprise Internet Communicator
- 7845GSMR Dual-Path Digital Wireless Communicator
- 7845i-GSM Triple-Path Digital Communicator
- Touchtone or pulse
- Formats supported
 - ADEMCO Contact ID
 - ADEMCO 4 + 2 Express
 - ADEMCO low speed
 - SESCOA/Radionics
- 3 + 1, 4 + 1 and 4 + 2 reporting
- Reporting capabilities
 - Split
 - Dual
 - Split/Dual – True dial tone detection
- Low battery reports 11.2 – 11.6VDC
- AC loss and restoral reporting supported

ORDERING

VISTA-15P

Control Panel

VISTA-15PSIA

Control Panel for CP-01 SIA certifications

Automation and Control Solutions

Honeywell Security & Communications
2 Corporate Center Dr. Suite 100
P.O. Box 9040
Melville, NY 11747
www.honeywell.com

L/VISTA15P/D
September 2008
© 2008 Honeywell International Inc.

Honeywell

www.BevanSecurity.Com